
USB TO RS232/RS422/RS485 CONVERTER

FEATURE

- USB 1.1 Compatible
- Communication speed is up to 115.2 kbps.
- Auto-baud rate; No need to set the baud rate of RS-485/RS-422
- Auto detect RS485/RS422 without any configuration
- 3KV Isolation between Power Module and Photo Coupler



ORDER INFORMATION



SPECIFICATION

■ Watch dog timer: Built-in hardware auto reset function
 ■ Serial communication: Transmission speeds: 300~115200 bps

Data bits: 7, 8 Parity: None, Even, Odd Stop bits: 1, 2 Flow control: RTS/CTS,

_ LED indication:SYS: Red high bright round LED
TX: Green high bright round LED

RX: Green high bright round LED

_ Terminator Resistance: 1200

_ Isolation: 3KV for 1 minute, Between Power & Ports

Power

_ Power Supply: No external power supply needed

■ Power consumption: ≤1W

Environmental

_ Operating temp.: 0~55 °C, non-condensing

_ Operating relative humi.: 20~95 %RH **_ Storage tem**perature: -10~70 °C

Mechanical


 ■ Case Materiel:
 ABS fire-protection (UL 94V-0)

 ■ Mounting:
 Surface mounting

 ■ Terminal block:
 Plastic NYLON 66 (UL 94V-0)

_ Weight: 150g

FRONT PANEL & CONNECTION DIAGRAM



DIMENSIONS

